

NX-P1202AV/P1302AU

2W VHF/UHF ANALOG PORTABLE RADIOS

Kenwood's ProTalk NX-P1202AV and NX-P1302AU portable two-way business radios deliver professional performance at an economical price point. Offering the ideal solution for communications in construction, manufacturing and warehousing, retail, hospitality, facility management and rental fleet applications. Engineered to provide superb ease of use and audio clarity, even in noisy environments and boasts rugged performance for dependable communications in all weather conditions. It's business done right!

FleetSync[®]



Simple Yet Tough

TOUGH & WATER RESISTANT ^{*2}

Built to take rough treatment in stride, the ProTalk has passed the demanding IP54/55 dust and water intrusion tests – both with and without the KMC-45 optional speaker microphone. It also meets or exceeds 11 stringent MIL-STD 8 10 C/D/E/F/G environmental standards, including "driven rain".

POWERFUL YET NATURAL SOUND OUTPUT

BTL audio amplifier for powerful 1-watt output.

Customize and Deploy

SECOND PTT

Make use of the Second PTT **feature by** giving different instructions to different staff as the radio allows the use of main channel plus another channel^{*1}.

SELECTABLE 7-COLOR LED

A large 7-color LED indicator on the top panel illuminates to notify multi-status functions. ^{*1}

CLONING

Customize the radio programming one time and use the optional Cloning Cable to rapidly program groups of ProTalk radios with the same settings.

Secure

Confidentiality in radio communications is a KENWOOD priority, and helping to maintain a high level of security in analog mode is a 16-code voice inversion scrambler.

Upgrade to Digital

COMPATIBLE WITH DIGITAL AND ANALOG

This radio allows to upgrade to digital at a later time if you decide to **transition** from analog (requires license key). It enables to have dual mode NXDN digital and analog combined operation.

ENHANCED AUDIO QUALITY

Based on decades of experience with professional and high quality audio products, the NX-P1000 can be customized to deliver the best digital audio to business radio users with various language backgrounds.

DIGITAL TECHNOLOGY PROVIDES SUPERIOR CLARITY IN EXTENDED COVERAGE

As RF signal strength weakens with distance, analog reception becomes increasingly noisy. NEXEDGE - NXDN digital modulation technology improves audio recovery in fringe areas, thereby "effectively" increasing the usable coverage compared to analog.

Other Features

- Voice Announcement • SCAN • VOX / Semi-VOX (headset required) ^{*1}
- Button Lock • Time-out Timer • Battery Saver^{*1} • Calling Alert • QT / DQT
- Compander • Adjustable Microphone Gain • Low Battery Warning

^{*1}: PC programming required.

^{*2}: All interfaces must be fully sealed with appropriate covers or by designated genuine accessories.

Accessories

All accessories may not be available in all markets. Contact an authorized Kenwood dealer for details and complete list of all accessories.

KNB-45L 2,000mAh/7.4V Li-Ion Battery Pack 	KSC-35SK Fast Charger For the KNB-45L/69L/82LCM (3-Hour) 	KRA-22/23 VHF/UHF Low Profile Helical Antenna 	KMC-45D Speaker Microphone 	KHS-31C C-Ring PTT Ear Hanger Headset 
KNB-69L 2,550mAh/7.4V Li-Ion Battery Pack 	KSC-43K Dual Chemistry Fast Charger For the KNB 29N/45L/69L/82LCM 	KRA-26/ 27 VHF Helical Antenna UHF Whip Antenna 	KHS-26 Earbud In-line PTT Headset 	KBH-10 Belt Clip 
KNB-82LCM 2,000mAh/7.4V, Intrinsically Safe Li-Ion Battery Pack 	KVC-22 DC Vehicular Charger Adapter 	KRA-41/42 VHF/UHF Stubby Antenna 	KHS-27A D-Ring In-line PTT Headset 	

Specifications

General	NX-P1202AV	NX-P1302AU
Pre-set Frequencies	151-159 MHz	451-470 MHz
Max. Channels per Radio	64 channels	
Number of Zones	4 zones	
Max. Channels per Zone	16 channels	
Channel Spacing		
Analog	25" / 12.5 kHz	
Power Supply	7.5 VDC ±20 %	
Battery Life (5-5-90)		
KNB-45L (2000mAh)	Approx. 11.5 hours	
KNB-69L (2550mAh)	Approx. 14.5 hours	
Operating Temperature(Radio only) ²	-22°F to +140°F (-30°C to +60°C)	
Frequency Stability (-30 to +60°C, +25°C Ref)	±0.5 ppm	
Antenna Impedance	50 Ω	
Dimensions	(W x H x D) Projections Not Included	
Radio with KNB-45L/82LCM	213 x 484 x 132 in (54 x 123 x 33.5 mm)	
Radio with KNB-69L	213 x 484 x 148 in (54 x 123 x 37.5 mm)	
Weight		
Radio Only	5.64 oz (160 g)	
Radio with KNB-45L/82LCM	9.88 oz (280 g)	
Radio with KNB-69L	10.41 oz (295 g)	
FCC ID	K44501000	K44501101

¹ 125 / 30 kHz in VHF/UHF Bands excluding T-Band are not included in the models sold in the USA or US territories.
² Operating temperature specification for a Li-ion battery is -10°C to +60°C [14°F to +140°F].

Specifications shown are typical and subject to change without notice, due to advancements in technology. Details and timing of firmware and software updates are subject to change without notice. Analog measurements made per TIA603. Specifications are measured according to applicable standards. All interfaces must be fully sealed with appropriate covers or by designated genuine accessories.

Receiver	NX-P1202AV	NX-P1302AU
Sensitivity	Analog @ 12.5/25 kHz (12 dB SINAD)	0.20 μV / 0.24 μV
Selectivity	Analog @ 12.5 / 25 kHz	68 dB / 74 dB
Intermodulation Distortion		70 dB
Spurious Rejection		70 dB
Audio Distortion		7%
Audio Output Power		1 W / 12 Ω (Internal Output) 500 mW / 8 Ω (External Output)
Transmitter	NX-P1202AV	NX-P1302AU
RF Power Output ² (High / Low)		2 W / 1 W
Spurious Emission		-70 dB
FM Hum & Noise		
Analog @ 12.5 / 25 kHz		40 dB / 45 dB
Audio Distortion		2%
Emission Designator		16K0F3E, 11K0F3E, 8K30F1E, 8K30F1D, 8K30F7W, 4K00F1E, 4K00F1D, 4K00F7W, 4K00F2D

FleetSync® is a registered trademark of JVCKENWOOD Corporation in the United States and/or other countries. NEXEDGE® is a registered trademark of JVCKENWOOD Corporation. ProTalk® is a registered trademark of JVCKENWOOD Corporation. AMBE+2™ is a trademark of Digital Voice Systems Inc. All other trademarks are the property of their respective holders.

MIL-STD & IP

MIL Standard	MIL 810C Methods/Procedures	MIL 810D Methods/Procedures	MIL 810E Methods/Procedures	MIL 810F Methods/Procedures	MIL 810G Methods/Procedures
Low Pressure	5001/Procedure I	500.2/Procedure I, II	500.3/Procedure I, II	500.4/Procedure I, II	500.5/Procedure I, II
High Temperature	5011/Procedure I, II	501.2/Procedure I, II	501.3/Procedure I, II	501.4/Procedure I, II	501.5/Procedure I, II
Low Temperature	502.1/Procedure I	502.2/Procedure I, II	502.3/Procedure I, II	502.4/Procedure I, II	502.5/Procedure I, II
Temperature Shock	503.1/Procedure I	503.2/Procedure I	503.3/Procedure I	503.4/Procedure I, II	503.5/Procedure I
Solar Radiation	505.1/Procedure I	505.2/Procedure I	505.3/Procedure I	505.4/Procedure I	505.5/Procedure I
Rain*	506.1/Procedure I, II	506.2/Procedure I, II	506.3/Procedure I, II	506.4/Procedure I, III	506.5/Procedure I, III
Humidity	507.1/Procedure I, II	507.2/Procedure II, III	507.3/Procedure II, III	507.4	507.5/Procedure II
Salt Fog	509.1/Procedure I	509.2/Procedure I	509.3/Procedure I	509.4	509.5
Dust	510.1/Procedure I	510.2/Procedure I	510.3/Procedure I	510.4/Procedure I, III	510.5/Procedure I
Vibration	514.2/Procedure VIII, X	514.3/Procedure I	514.4/Procedure I	514.5/Procedure I	514.6/Procedure I
Shock	516.2/Procedure I, II, V	516.3/Procedure I, IV	516.4/Procedure I, II, V	516.5/Procedure I, IV	516.6/Procedure I, IV

International Protection Standard
 Dust & Water Protection* IP54/55* *To meet IP54/55, the 2-pin connector cover has to be connected on the radio or the locking bracket has to be attached to the external speaker microphone.

JVCKENWOOD USA Corporation
 Communications Sector Headquarters
 1440 Corporate Drive | Irving, TX 75038
 Order Administration/Distribution
 P.O. BOX 22745, 2201 East Dominguez St., Long Beach, CA 90801-5745
www.kenwood.com/usa

JVCKENWOOD Canada Inc.
 Sede central y distribución canadiense
 6070 Kestrel Road, Mississauga, Ontario, Canada L5T 1S8
www.kenwood.com/ca

KENWOOD Communications
 Global Website



comms.kenwood.com




ISO9001 Registered
 Communications Systems Business Unit
 JVCKENWOOD Corporation